

Introduction to Spallation Neutron Source

CSNS, Institute of High Energy Physics
Sheng Wang

Sep. 9, 2025







Outline




- 1. Neutron and neutron scattering
- 2. Introduction to Spallation Neutron Source
- 3. China Spallation Neutron Source
- 4. CSNS accelerators
- 5. Upgrade project CSNS-II



Neutron and neutron scattering

Neutrons are everywhere






Protons: 40kg

❖ Neutrons: 32kg

Electrons: 22g

Free neutrons





Reid, R.V. (1968). Annals of Physics. 50: 411-448

The discovery of neutron





1920

Noting that atomic number (Z) does not correspond to atomic weight (A), Rutherford suggests that, in addition to "bare" protons, the nucleus contains a heavy neutral particle.




1930

Bothe and Becker discover a penetrating, neutral radiation when alpha particles hit a Be target.

$$\alpha + {}^{9}Be \rightarrow {}^{12}C + n$$



1931




The discovery of neutron






James Chadwick 1932



J. Chadwick, Proc. Roy. Soc., A 136 692 (1932)

Neutron: the perfect tool for atomic studies






Atomic Structure and Dynamics Determine the Macroscopic Properties of Matter

1994 Nobel Prize in Physics -- Shull and Brockhouse





Applications of Neutrons



Neutron is an indispensable tool for material science study


"If the neutron had not been discovered by Chadwick in 1932, it would have been invented." --Brockhouse '94 Physics Nobel Prize



Neutron and X-ray



Neutron Scattering and X-rays: powerful complementary tools for studying material structure and dynamics





Neutron interacts with nucleus


X-ray interacts with e-cloud

A dispensable Research Platform









high penetration

magnetic moment

Sensitivity to Light Elements:

Deep stress detection

Atmospheric Neutron


Nuclear Data

New Energy Materials Supercond -ucting Materials














Spallation Neutron Source

Production of neutrons




Fission Reactors

- Chain reaction
- Continuous
- 2-3 neutrons/fission
- ~180MeV/neutron



Spallation


- No chain reaction
- Pulsed
- 30-40 neutrons/proton
- ~30MeV/neutron



The First Artificial Neutron Beam










Chicago Pile 1, CP1, 1942


History neutron source






Spallation neutron source in the world





Basic Components and Principles of a Spallation Neutron Source (Short pulse)




UK: ISIS



- Started from 1980
- 160+32kW

Two target stations






US: SNS



• Started from 1998, 6 institues, 8 years, \$1.4B

Now operating with 1.7MW



Japan: J-PARC




Started from 2001, design beam power 1MW, \$2B, finished at 2009

Including a 30GeV synchrotron for high energy physics



China: CSNS





 Start from 2011,design beam power 100kW, \$0.3B, finished at 2018

Spallation neutron source



Machine	Energy [GeV]	Intensity [ppp]	Tune-shift	Rep-rate [Hz]	Power [MW]	Type
ISIS	0.07-0.8	2.5x10 ¹³	~0.4	50	0.2	RCS
J-PARC	0.4 - 3.0	0.8x10 ¹⁴	0.15	25	1.0	RCS
SNS	1.0	1.6x10 ¹⁴	0.1	60	1.0	AR
CSNS	0.08-1.6	1.56x10 ¹³	0.28	25	0.1~0.5	RCS
ESS	1.0	2.3x10 ¹⁴		14	1	LINAC



China Spallation Neutron Source

Location of CSNS





CSNS campus







- **♦** Proposed at year of 2000
- Budget: about 2.2 B CNY
- Construction started at Sep. 2011,
 and finished at Mar. 2018
- User program started in Oct. 2018
- Beam power increased from 20kW to 170kW
- Operation with long user hours and high availability
- ◆ 11 neutron instruments and in user program

CSNS Facility






Beam Power on target [kW]	100
Proton energy [GeV]	1.6
Average beam current [uA]	62.5
Pulse repetition rate [Hz]	25
Linac energy [MeV]	80
Linac type	NC
Linac RF frequency [MHz]	324
Macropulse duty factor	1.05
RCS circumference [m]	228
RCS harmonic number	2




Back-n White neutron source






CSNS Beam Power History





Neutron Instruments






3 in trail user operation


User Program




https://user.csns.ihep.ac.cn (in both Chinese and English)

- Registration user: 8000+ (130+ abroad)
- A total of over 2,000 projects from ~240 units were completed, with industry users comprising approximately 10% of the total.
- Two rounds of proposal calls each year








Research Areas









CSNS Accelerators: Design and Commissioning

CSNS accelerators







The Evolution of Beam



	Beam	Kinetic Energy (GeV)	Emittance/ Acceptance (πmmmrad)	Peak Current	Bunch Length	Beam Power (kW)
LRBT	H-	0.08	4/25	15mA	~ 500µs	5
Injection	H⁻→p	0.08	300/540			5
RCS	p	0.08 →1.6	300 →80/540			5 →100
Extraction	p	1.6	~ 80/350	~ 3.5A	80ns+80ns	100
RTBT	p	1.6	~ 80/350	~ 3.5A	80ns+80ns	100

Average current 62.5µA

Beam at the exit of Linac

Beam at the target

Space charge effects



Let two charged particles move parallel with same velocity, then electric field and magnetic field experienced by particles are

$$E = \frac{q}{4\pi\varepsilon_0 d^2}$$

$$B = \frac{\mu_0 q v}{4\pi d^2}$$

Where q is charge, ε_0 the dielectric constant, μ_0 the permeability, vthe velocity.

The ratio of magnetic and electric forces is

$$\frac{F_m}{F_e} = \frac{v^2}{c^2} = \beta^2$$

For non-relativistic beam, *Fm*<< *Fe.* Due to the signs of *Fm and Fe* are inverse, the space charge effects are decreased with the increase of the velocity.

Space charge tune-shfit



Space charge is a fundamental limit to beam power in high intensity AR and synchrotron. The incoherent space-charge tune shift is

$$\Delta v_{x,y} = -\frac{f_{sc}Nr_0R}{2\pi B_f v_{0x,y}\beta^2 \gamma} \left[\frac{1}{\sigma_{x,y}(\sigma_x + \sigma_y)} (\frac{1}{\gamma^2} - \eta_e) + A_{im}^e (\frac{1}{\gamma^2} - \eta_e) + A_{im}^m \right]$$


The contribution from the electric and magnetic images of the beam are represented by the Laslett tune shifts $A_{im}^{\ e}$ and $A_{im}^{\ m}$, respectively. For a round beam with no neutralization, the direct space-charge tune shift becomes

$$\Delta v_{x,y} \approx \frac{f_{sc} N r_0}{4\pi B_f \varepsilon_{rms} \beta^2 \gamma^3}$$

Where N is the proton number, r_0 is the classical radius of a proton, The bunch form factor fsc is equal to 1/2 for a uniform distribution, and to 1 for a Gaussian distribution. The B_f is bunching factor. $\epsilon \text{ rms} = \sigma 2/\beta 2$, $\beta = R_0/v_0$

Front end and Linac






CSNS-RFQ




Output energy	3.0 MeV	
Repetition rate	25 Hz	
Pulse H- beam width	500 μs	
Pulse H- beam current	40 mA	
RF Freq.	324MHz	
Length	3.5	



Field tuning (before)






Field tuning (after)

Drift Tube Linac (DTL)








	DTL		_			
Length	35.44	m	-			
Frequency	324	MHz	-			
Beam energy	3-80.1	MeV	-			FFDD
Number of Tanks	4		FFDD	FFDD	FFDD	——————————————————————————————————————
Copper RF power	5.3	MW				
Peak current	15	mA	Rb=0.8cm	Rb=1.0cm	Rb=1.0cm	Rb=1.2cm
Aperture radius	8-12	mm				
Number of Cells	161		-			

DTL FFDD Lattice











Design of drift tube






Cell geometry



- 9 different profiles of drift tube were adopted based on the optimization on ZTT and kilpatrick.
- The DT Face angle varies from 0° to 60° to reach a relatively high ZTT and a tolerable kilpatrick,

Characteristics of RCS






RCS design



- RCS may be divided into various systems according to their beamhandling functions
 - Injection
 - Capture and acceleration
 - Extraction
 - Collimation, and transport
 - Beam instruments and correctors
- These systems are integrated by the 'lattice' magnets, usually symmetrically arranged to alleviate the lower-order resonances


- Separated-function design
- ➤ The collimation be performed in a separate straight section.
- The superperiodicity of 4 is better for reducing the impact of low-order structure resonance than the superperiodicity of 3.



A Lattice with Triplet Cells




- > Four-fold symmetry
 - Separated functions
- **➤** Triplet structure
 - Small magnet aperture
- > Dispersion-free long uninterrupted straight
 - For collimation & injection/extraction
- > Straight at arc with large dispersion
 - High efficiency momentum collimation
- ➤ The all-triplet structure is not good for chromaticity correction and dynamic aperture



A Lattice with Triplet Cells




Circumference (m)	227.92
Superperiod	4
Number of dipoles	24
Number of quadrupoles	48
Lattice structure	Triplet
Total Length of long drift (m)	3.85*8+11*4
Nominal Betatron tunes (h/v)	4.82/4.80
Chromaticity (h/v)	-4.3/-9.2
RF Freq. (MHz)	1.02~2.44
RF Voltage (kV)	165
Trans. acceptance (μπm.rad)	540
Momentum acceptance	1%
Effective length of dipoles(m)	2.1
Dipole gap (mm)	160
Max. quadrupole aperture (mm)	265
Number of quadrupole power supplies	5 47



Tune Diagram for 4-fold Structure





red: 1st order structure resonance

golden: 2nd order structure resonance

blue: 3rd order structure resonance

green: 4th order structure resonance

gray: 3rd deference structure resonance


pink: coupling resonance

$$mQ_x + nQ_y = 4l$$

m, n=0,
$$\pm 1$$
, ± 2 , ± 3 , ...

Chromaticity Correction







- Powered with DC power supply
- 2 families power supplies
- Designed for low beam density
 - for commissioning

Dynamic aperture







 $4.5\sigma x \times 2.5\sigma y$, $\Delta p/p = \pm 1\%$ with sextupoles $2.5\sigma x \times 2\sigma y$, $\Delta p/p = \pm 1\%$ with sextupoles and high order field of dipoles and quadrupoles σx and σy are h and v beam size ($320\pi mm.mrad$)


Longitudinal dynamics



- The RF cavities with harmonic number of 2 are adopted;
- Dual harmonic cavities will be added in the future upgrade for higher beam power;
- 8 RF cavities provide total RF voltage of 165 kV, with one additional cavity for redundancy.
- The design of RF voltage and phase curves is an important issue to decrease the beam loss due to the space charge and phase changes


RF voltage and phase





The Longitudinal Phase Space






Beginning of acceleration

End of acceleration


Two-stage beam collimation






H- stripping Painting injection





RCS injection design





Injection component layout. BC1~BC4: Fixed orbit bump magnets , BH1~BH4: horizontal painting bumpers, BV1~BV4: vertical painting bumpers, ISEP1&2: septum


Intense beam effects in RCS commissioning (SNS)



Beam power on target	Challenges	Solutions
50kW→80kW	Too large beam size after painting, non-uniform beam distribution, large transverse coupling	By using the correlated painting instead of the anti-correlated painting
80kW→100kW	Serious beam instability	Optimization of the tune and chromaticity
100kW→125kW	Emittance increase caused by broken four-fold symmetry of the RCS; Stranger beam instability	Slight modification of injection system; installation of AC trim quadrupoles and AC sextupoles
125kW→170kW	Strong space charge effects	Installation of a dual harmonic RF cavity

Tune Pattern Optimization






0.75

4 6 Time (ms) 10


Painting scheme optimization





Super-periodicity restoration








The duel harmonic RF system





- ➤ The dual harmonic system is designed for ease the space charge effect in the upgrade of CSNS
- ➤ The prototype MA cavity was installed and operated online
- > The initial use of dual harmonic system effectively reduces beam loss and increases beam power.












Bunching factor with r and dp/p

Optimization of Dual RF pattern

Collective instability in RCS




- ➤ With nominal tune (4.86/4.78) and nature chromaticity, coherent oscillations were observed when beam power >50 kW, with amplitude increasing as the intensity increases.
- ➤ The growth time is less than 1 ms for 100 kW
- \triangleright The impedance is several handred k Ω /m
- ➤ It is a "broadband" impedance




Mitigation of instability

SNS

- ➤ The coherent oscillation was damped by increasing chromaticity (DC sextupoles)
- ➤ Optimizing tune pattern to mitigate the coherent oscillation




✓ With two mitigation methods, the beam power reached 100 kW successfully.



Upgrading sextupoles for high beam power




- > DC sextupoles were replaced by AC after beam power reached 100kW (in 2021)
- With AC sextupoles, the chromaticity can be well controlled in an RCS cycle
- > AC sextupole plays a crucial role in beam power of 100 kW+
- > AC sextupoles made significant contribution from 100KW to 170 kW
- The instability can be completely suppressed with beam power of 170 kW



DC and AC sextupole field.

The head-tail mode with different chromaticities



Coherent oscillation well controlled in the commissioning

Possible source of impedance



- ➤ Many studies have been done on the collective instability in design stage, but this instability is unexpected.
- ➤ Measurements revealed that the ceramic vacuum chamber exhibits low-frequency resonance.
- ➤ The further study confirmed that the impedance originates from the shielding layer of the ceramic vacuum chamber.





Figure 2: Illustration of the cross-sectional view of the ceramic chamber.








Without RF shield/screen



China Spallation Neutron Source-II

China Spallation Neutron Source-II





- ➤ Project Budget: 2.9 B CNY
- Funded by central andGuangdong local government
- Design and R&D completed
- Construction: 2024.1~2029.10(5 years and 9 months)


Beam Power Upgrade (two-step)



- 1. Linac (80MeV) + RCS upgrade 150~200kW (the first step)
 - ✓ New dual harmonic RF system
 - ✓ Adding AC trim quadrupoles, sextupoles and octupoles
 - ✓ New injection region
- 2. Linac (300MeV+) + upgraded RCS 500kW (the second step)
 - ✓ SC linac to 300MeV
 - ✓ Upgrade the power supplies for main magnets

The Front End of CSNS Accelerator





H- ion source, LEBT, chopper, RFQ

- The LEBT has 3 solenoids, initially designed for the former penning ion source.
- The penning source has been replaced by RF-driven H⁻ ion source in Sep. of 2021.
- The ion source current is up to 60mA, and throttled to the required value.
- New LEBT and new RFQ for CSNS-II is under construction and test in the lab.


RF Driven H- Ion Source



Typical operation parameter


	CSNS service	Test bench study
Peak RF-power	31 kW	25~40kW
H2 flow rate	21 SCCM	18~24 SCCM
Repetition rate	25 Hz	25 Hz
Plasma pulse width	680 μs	500~1000μs
Beam pulse width	498 μs	100~600 μs
H- peak current	37 mA	50~60mA
Cs reservoir temp	80~87C	77~120°C
Service cycle	>330days	
Beam energy	50 keV	50 keV
Norm. RMS emitt.	Not measured	0.31π@60mA

The RF ion source installed in the tunnel




New LEBT for CSNS-II





RFQ inlet plane


LEBT for CSNS-II



Parameters	CSNS LEBT	CSNS-II LEBT
Length	1668mm	738mm
Inner diameter	138mm	64mm
RFQ inlet current	~40mA	60mA
RMS Emitt. @RFQ inlet	0.307@37mA	0.24@52mA
Num. of solenoids	3	2
Length of solenoids	240mm	127mm
Stripped proton removal	No deflection	1.8 degree (3.6 to H-)
Chopper length	50mm	27mm
Chopper voltage	3.8~5kV	6~8kV

Linac Upgrade






	CSNS	CSNS- Ⅲ
Particle species	H-	H-
Pulse repitition frequency(Hz)	25	25+25
Linac beam energy (MeV)	80	300
Average current(μA)	62.5	625
Peak current (mA)	15	50
Pulse width(μs)	500	500

Special requirements;

- ♦ Energy spread: <0.03%
 </p>
- → High availability (>97%)

Beam dynamics- ϕ_s and E_{acc}






$$k_{l0}^{2} = 2 \times (\phi_{s})_{324MHz}$$

$$= \frac{2\pi q E_{0} T sin(-\phi_{s})}{mc^{2} \beta_{s}^{3} \gamma_{s}^{3} \lambda},$$

 $maximum\ variation\ per\ period < 2deg/m$

Beam dynamics-lattice







- Zero-current phase advance per period should be less than 90 degrees to avoid parametric resonances.
- Average phase advance per meter should be continuous to avoid mismatch.

Multi-particle tracking results






Emittance evolution along the MEBT+DTL+SC



- ➤ The RMS emittance growth through MEBT+DTL+SC is 26%(horizontal), 32%(Vertical) and 32%(longitudinal).
- ➤ Halo parameter is less than 2.2, and the tune depression is bigger than 0.4

Horizontal testing

See Huachang's report



- ✓ The successful integration of the cryostat and the completion of the high-power conditioning process for the couplers mark significant milestones.
- ✓ Horizontal testing yielded promising results with a maximum gradient of 15.2 MV/m and a static heat load of 16.3 W.
- ✓ Further measurements are required to accurately determine the dynamic heat load.

6-cell Elliptical cavity




• 648 MHz 6-cell Elliptical Cavity

	1				
parameter	design				
Frequency(MHz)	648				
TTF@ β_g	0.7				
$oldsymbol{eta}_{ extsf{g}}$	0.62				
E_p/E_{acc}	2.53				
$B_p/E_{acc}(mT/(MV/m)$	5.45				
R/Q (Ω)	309				
G (Ω)	177				
Beam tube diameter (mm)	105/120				
Cell-cell coupling (%)	1.35				
$E_{acc}(MV/m)$	14				



mechanical structure of prototype ellipsoidal cavity




The flatness of the electric field is 97.9%.





BCP and HPR



During testing, the highest gradient reaches 21.7 MV/m


Debuncher System



Two Debuncher cavities:

- **□ DBUNCH-1** reduces beam energy jitter
- □ DBUNCH-2 controls energy spread






Parameters	Value		
Beam Energy at the End of SC Linac	300 MeV		
Repetition Frequency	50Hz		
Debuncher Cavity-1 Frequency	648 MHz		
Debuncher Cavity-1 Aperture	70 mm		
Debuncher Cavity-1 ETL	3.3 MV		
Debuncher Cavity-2 Frequency	648 MHz		
Debuncher Cavity-2 Aperture	70 mm		
Debuncher-Cavity-2 ETL	1.0 MV		
Reducing Ratio of Momentum Jitter	77.3%		
Minimum $\Delta P/P$ at the end of Linac (99.5%)	0.35‰		

New injection scheme for CSNS-II





BC BH BCH

Angular scanning

Position scanning

Chicane Horizontal
bump painting bump

New idea: chicane bump and horizontal painting bump are combined into one bump which make the chicane bump "move". The horizontal painting is performed by using the position and angle scanning at the same time.


Advantages:


- ◆Peak temperature of the stripping foil can be greatly reduced.
- ◆Both correlated and anti-correlated painting can be performed.
- ◆The edge focusing effect of bump magnets is greatly reduced
- ◆The difficulty of large aperture of the injection port and transport line required by angular scanning is solved.
- ◆It saves a set of bump magnets and is easier to optimize the layout of the injection system.

Description for the new painting scheme





Correlated painting





Anti-correlated painting






- **Injection beam**: BCH is used for horizontal angular scanning, while the horizontal position is also scanned in a small range.
- **Circulating beam:** horizontal and vertical position scanning can be performed with BCH and BV magnets.
- Residual H⁰ beam: H⁰ beam at the waste beam outlet has an angle distribution with time. A small pulse magnet is installed for angular scanning compensation.
 - Compatibility mode for correlated and anticorrelated painting: match the angle of SEP and BCH magnets.
 - **Spatial optimization**: BCH bump is irregularly shaped to allow the waste beam line to move a short distance along outside the RCS.

BCH bump and key magnets




Correlated painting



Scanning angle: 4.5 mrad

Anti-correlated painting



Scanning angle: 5.0 mrad

Painting	Time	SEP1 (mrad)	BCH2 (mrad)	BCH3 (mrad)	BCH4 (mrad)	LRBD (mrad)	SEP2 (mrad)	INDB1 (mrad)	INDB2 (mrad)	BCH1 (mrad)
Correlated	Begin	226.713	53.549	64.681	60.181	-4.5	349.82	-13.419	-34.356	58.049
	End	226.713	49.049	60.181	55.681	+4.5	349.82	-13.419	-34.356	53.549
Anti-correlated	Begin	222.32	58. 442	58. 442	58. 442	-5	351.558	-13.066	-34.708	58.442
	End	222.32	53. 442	53. 442	53. 442	+5	351.558	-13.066	-34.708	53.442

Upgrade of RCS Injection System











CSNS-II Injection Installing...


CSNS Injection

Jun. 20- Aug.31

MA Cavity




- 1.8m 3 gaps water-cooling cavity with external diameter 850mm MA rings
- 2 cavity were put into operation in 2022 and 2023
- Gradient >50kV/m on second hormonic mode (15% duty factor)
- Gradient >25kV/m on fundamental hormonic mode (50% duty factor)
- Cavity impedance is stable after long-term operation (variation < 3%)



Neutron Instruments for CSNS-II





Location	Instrument
BL01	Small Angle Neutron Scattering
BL02	Multiple Purpose Reflectometer
BL03	Liquids Neutron Reflectometer
BL04	Cold Neutron Inelastic Spectrometer
BL05	High Energy Direct Geometery Inelastic Spectrometer
BL06	Molecular Vibrational Spectrometer
BL07	Reserved
BL08	Engineering Material Diffracmeter
BL08A	Neutron Technology Testing Station
BL09	High-resolution Neutron Powder Diffractometer
BL10	Neutron Backscattering Spectrometer
BL10A	Reserved
BL11	Atmosphere Neutron Irradiation Spectrometer
BL12	Neutron Physics and Application Instrument
BL13	Energy-resolved Neutron Imaging Instrument
BL14	Very Small Angle Neutron Scattering Instrument
BL15	High Pressure Neutron Diffractometer
BL16	Multi-Physics Instrument
BL17	Elastic Diffuse Scatting Spectrometer
BL18	General Purpose Powder Diffractometer
BL19	Single Crystal Neutron Diffractometer
BL20	PolArized Chopper Spectrometer


CSNS-II New Buildings





Progress of Civil Engineering














CSNS-II CPM



During the construction period, the open operation is minimally impacted due to the implementation of a well-planned installation and commissioning plan.



Plans to maintain user operation almost unaffected during CSNS II construction

